



**marantz®**

## Product information

### NR1402 - 5.1CH AV RECEIVER WITH SETUP WIZARD



Users who do not need the network functionalities or USB features of its bigger brother, will find their ideal AV centre with the NR1402. The second slim-line AV Receiver in this year's line-up also offers a line-up of clever features.

The NR1402 comes, among others, with on-board decoders for Dolby TrueHD and DTS-HD Master Audio, while its four HDMI 1.4 inputs (with 3D support) handle a multitude of digital sources for an easy hook-up of satellite boxes, BD/DVD players or game consoles. All at the same time. The 5x 50W discrete powered channels can be used for a simple stereo setup but is also powerful enough to run a full 5.1 system creating spectacular surround sound. It all adds up to a fabulous sound with great video quality, wrapped together in an elegant slim-line design.

#### Main Features

- Low profile chassis
- 7x 50 Watts 8 ohms RMS
- Audyssey MultEQ, Dynamic EQ and Dynamic Volume
- 4in / 1out HDMI 1.4 (3D)
- Front Auxiliary input for iPod/iPhone
- Transparent GUI and multilingual setup wizard
- Pre-programmed RC

#### EAN

|           |             |               |
|-----------|-------------|---------------|
| <b>EU</b> | NR1402/N1B  | 4951035044629 |
|           | NR1402/N1SG | 4951035044636 |
| <b>UK</b> | NR1402/T1B  | 4951035044759 |
|           | NR1402/T1SG | 4951035044766 |

# because music matters



marantz®

## NR1402 - 5.1CH AV RECEIVER WITH SETUP WIZARD



| FEATURES   | NR1402          |
|--|-----------------|
| <b>MULTICHANNEL SURROUND</b>                                   |                 |
| DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24                   | o / o / o / o   |
| Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz | o / o / o / -   |
| Audyssey DSX   | -               |
| Multichannel Stereo  | o               |
| Dolby Headphone  | -               |
| Compressed audio Enhancer: MDAX / MDAX2                        | - / o           |
| <b>SOUND ENHANCEMENTS</b>                                      |                 |
| Current Feedback Topology                                      | -               |
| Hyper Dynamic Amplifier Modules (HDAM)                         | -               |
| High Grade Audio Components                                    | -               |
| <b>NETWORK</b>   |                 |
| DLNA Certified   | -               |
| Network Audio: MP3 / WAV / AAC / FLAC / FLAC 96/24 / WMA       | -               |
| Internet Radio: direct / external media player                 | -               |
| vTuner / Napster* / last.fm*                                   | -               |
| Ethernet   | -               |
| <b>OTHERS</b>  |                 |
| Bluetooth audio via RX101                                      | optional        |
| Auto speaker setup by microphone                               | Audyssey MultEQ |
| Audyssey Dynamic EQ / Dynamic Volume                           | o / o           |
| Video conversion   | -               |
| Analogue to HDMI scaling                                       | -               |
| HDMI to HDMI scaling   | -               |
| Videoprocessing  | -               |
| Picture adjust / Noise reduction                               | - / -           |
| HDMI path though on stand-by                                   | o               |
| 3D video pass through  | o               |
| Audio Return Channel   | o               |
| On Screen Display: GUI / OSD                                   | o / -           |
| GUI overlay on HDMI  | o               |
| Setup Wizard (ENG, GER, FR)                                    | o               |
| Variable cross over  | o               |
| Multiroom zones  | -               |

| <b>INPUTS/OUTPUTS</b>  |                   |
|--|-------------------|
| <b>VIDEO</b>   |                   |
| Composite In / Out   | 3 / 1             |
| Component In / Out   | 2 / 1             |
| HDMI In / Out (version x.x)                                  | 4 / 1 (1.4)       |
| Multi-Room Video Out: Video / Component                      | - / -             |
| <b>AUDIO</b>   |                   |
| Analogue In / Out  | 4 / 0             |
| Phono (MM) In  | -                 |
| Digital Optical In / Out                                     | 1 / 0             |
| Digital Coaxial In / Out                                     | 1 / 0             |
| Multichannel Pre Out / Main In                               | o (2.1) / -       |
| Subwoofer Out  | 1                 |
| 7.1 multichannel input                                       | -                 |
| <b>OTHER</b>   |                   |
| M-XPort for RX101  | o                 |
| Speaker A / B  | -                 |
| Height speaker terminal                                      | -                 |
| Bi-amp drive (5.1 ch setting) / Speaker C                    | - / -             |
| Multi-Room Speaker Terminal                                  | -                 |
| Marantz remote bus   | o                 |
| IR Flasher In  | -                 |
| Network: (IP-control / update)                               | - / -             |
| RS232C (control / update)                                    | - / -             |
| DC Triggers  | -                 |
| Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB | o / - / - / - / - |
| USB Audio / Made for iPod / Works with iPhone                | - / - / -         |
| <b>SPECIFICATIONS</b>  |                   |
| Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)        | 50 W              |
| 70% Guarantee  | -                 |
| Audio Signal to Noise Ratio                                  | 98 dB             |
| FM Tuner   | o                 |
| <b>GENERAL</b>   |                   |
| Available colors: Gold / Silver / Black / Silver-Gold        | - / - / o / o     |
| Metal Front Panel  | -                 |
| System Remote Control  | RC013SR           |
| Pre-programmed / Learnable / LCD Display                     | o / - / -         |
| Power Consumption in W                                       | 180               |
| Standby Consumption in W                                     | 0.2               |
| Maximum Dimensions (W x D x H) in mm                         | 440 x 367 x 105   |
| Weight in kg   | 8.2               |

\* Not available in all regions

Design and specifications are subject to change by Marantz without notice.

# because music matters