

# specifications

Continuous power output (20Hz—20kHz at 0.5% THD), per channel	
Both channels, 8Ω, 20Hz—20kHz	75W
Single channel, 4Ω, at 1kHz	130W
Harmonic distortion, 80% power, 8Ω at 1kHz	0.004%
Inputs	
Phono cartridge:	
Input sensitivity at 1kHz	2.5–15mV (user adjustable)
Input impedance	47kΩ
Signal/noise ratio (CCIR, 65W)	88dB
Overload margin	31dB
Line and AV inputs:	
Nominal sensitivity	250mV–1.5V (user adjustable)
Input impedance	22kΩ
Signal/noise ratio (CCIR, 65W)	98dB
Preamplifier output	
Nominal output level	630mV
Output impedance	<50Ω
Headphone output	
Maximum output level into 600Ω	7V
Output impedance	100Ω
General	
Mains voltage	110-120V or 220-240V
Power consumption (maximum)	650VA
Power consumption (standby)	2.5VA
Dimensions W x D x H (including feet)	432 x 275 x 85mm
Weight (net)	8.5kg
Weight (packed)	10.4kg
Supplied accessories	mains lead CR90 remote control 4 x AAA batteries
E&OE	
<b>NOTE:</b> All specification values are typical unless otherwise stated.	

## Continual improvement policy

Arcam has a policy of continual improvement for its products. This means that designs and specifications are subject to change without notice.