



SR-4021

STEREO RECEIVER



This stereo receiver is built to the highest standards and expertly finished. Incredible attention to detail and no compromise construction ensures they faithfully capture the excitement and emotion of your kind of music. The SR-4021 is the pure high performance stereo receiver, with an RDS tuner with FM/AM reception, 30 random presets and a powerful 2 x 80 Watt stereo amplifier at its heart. The phono MM preamplifier makes it easy to connect a turntable. Its extensive AV switching capabilities and the speaker A/B feature make it a true centre piece of your stereo system. The metal chassis and solid metal front panel provide a rigid base for high quality performance

- 2 x 80 Watts (8 Ohm RMS) power amplification
- RDS FM/AM tuner with 30 random presets
- Solid metal front panel and rigid chassis construction
- Symmetric circuit architecture
- Separate solid heatsinks
- Tone control and Source Direct function
- Pre-output and main-input for upgrade possibilities
- Eight audio inputs including Phono (MM)
- Video switching via three audio / video inputs and a monitor output
- Sleep and timer function
- Speaker A/B
- Flasher In for system integration (direct connection to RX-7001)
- System remote control and Marantz D-Bus



CR-401

CD-RECEIVER



High fidelity stereo is now available in an integrated compact system with tuner, amplifier and CD player in one compact box. Advanced functionality, such as DAB and MP3 playback, perfectly complements top-quality sound and superb performance. A fabulous audio experience that also saves space.

- High quality CD-Receiver system
- 2 x 30 Watts (6 Ohm RMS) discrete power amplification
- Stereo FM and AM reception
- RDS function with station name and radio text indication
- Solid metal front panel and rigid chassis construction
- Easy to use button layout on front panel operation
- High quality playback of almost any 12 cm disc including CD, CD-R/RW
- MP3 playback including text information
- Clock and Sleep timer function
- Headphone output
- Tone control and source direct function
- 3 line in and 2 line out plus digital optical output
- Subwoofer pre-out
- Dedicated remote control and Marantz D-Bus

Stereo Receiver

AMPLIFIER FEATURES

Current Feedback Topology	-
Linear Drive Power Supply	-
CCNE	-
Power Transformer: Super-ring / Toroidal / EI	-/•
HDAM: Standard / SA / Current Feedback	-
HDAM cover: Gold plated / Copper plated / Metal / no shield	-
Symmetric PCB Layout	•
High Grade Audio Components	-
Customised Components	-
Current Feedback phono equalizer	-
Balance / Bass / Treble / Loudness	•/•/•/-
Source Direct	•
Separate Solid Heat Sinks	•
Speaker A/B	•
Record Selector: full / copy-source	-/•
Tape Monitor	-
Phono Input	•
Standby Mode	•
Display dimmer	•
RS232C (control / update)	-/-

TUNER FEATURES

DAB SECTION

Receiving Range (Band III / Band L)	-/-
Signal to Noise Ratio (Mono/Stereo)	-/-
DAB presets	-

TUNER SECTION

Broadcast bands: FM / MW / LW	•/•/-
Dual Gate MOS-FET	•
Phase Lock Loop Synthesizer	-
IF Bandwidth Selector	-
High Alternate Channel Selectivity	-
Presets	-
Auto Tuning	30
RDS: PTY/PS/CT/TA/TP	•/•/-/•
RDS: EON	-
Station Naming	•
Sleep / Timer	•/-
Birdy Whistle Elimination Circuitry	•

INPUTS/OUTPUTS

Audio Inputs	8
Phono Input: MM/MC	•/-
Audio Outputs	3
Video inputs	4
Video outputs	2
Digital In / Out	-/-
Processor In / Out	-/-
Pre-out / Main-in	•/•
FM Antenna	1
AM Antenna	1
D-Bus In/Out	•
Gold Plated Cinch	-
Speaker Terminal: Click-fit / Screw / WBT	-/•/-
AC Outlets (Not for UK Model)	-
Headphone Out	•
I-Pod input (direct / docking station)	-/•

SPECIFICATIONS

AUDIO SECTION

Power Output (8/4 Ohm RMS)	80/- W
Frequency Response	10Hz - 65 kHz (-3dB)
Total Harmonic Distortion	0,08%
Damping Factor	N/A
Input Sensitivity: MM	2.6mV
Input Sensitivity: MC	-
Signal to Noise Ratio MM/MC	>70 dB
Input Sensitivity: High level	200 mV / 47 kOhm
Signal to Noise Ratio High Level	>95 dB

VIDEO SECTION

Input level/impedance	1Vp-p / 75 ohm
Output level/impedance	1Vp-p / 75 ohm
Video frequency response	5 - 30 MHz
Signal to Noise Ratio	>60 dB

GENERAL

Available colors:	-/•/•
Platinum/Gold/Silver/Black	
Metal Front Panel	•
Remote Control	RC4021SR
System Remote Function	•
Power Consumption	220 W
Detachable Power Cable	•
Maximum Dimensions (W x D x H)	440 x 388 x 163 mm
Weight	11.7 kg