



SR5007 NETWORK AV RECEIVER



The SR5007 also features the famous Marantz circular display, and it has the same networking facilities for audio streaming from PC and Android, Internet radio, online services and AirPlay from your iPhone, iPad or iPod. It also includes decoders for standard audio as well as for Dolby TrueHD and DTS-HD Master Audio. And, it comes with no less than six HDMI inputs of which one is on the front – making it immediately ready for 3D/4k video and ARC (Audio Return Channel) from ARC-compatible TV sets. Lower resolution video can be up-scaled to 4k too. It easily handles the most demanding of scenes in action films, as well as offering excellent-quality music playback, thanks to the latest Marantz audio technologies. To ensure you get the best possible audio with compressed files from iPod via USB, the SR5007 offers 7x 100W rms and incorporates the M-DAX2 – Marantz Dynamic Expander version2. This neat little addition also optimises the quality of MP3 files from either CD or the optional Bluetooth Receiver RX101. Everything sounds clearer, more detailed, and more alive. To finish off, the SR5007 comes with a whole range of convenience features such as: Setup Assistant, “auto calibration” with Audyssey MultiEQ XT and Dynamic Volume Control; “Multi-Room” with multi-source flexibility; and “video-off” mode to ensure you enjoy your music and your movies in true dynamic Marantz style. It also has the specially developed Marantz Remote App for iPhone and Android devices. All of which makes the SR5007 a true combination of style, power and ease.

Main Features

- Discrete power amplification of 7x 100 Watts 8 ohms RMS
- Full 4k compatibility – Scaling – Pass through – GUI overlay
- DLNA1.5 Network audio streaming and Internet radio
- AirPlay and music services Spotify and last.fm installed
- Audyssey MultEQ XT, Dynamic EQ and Dynamic Volume
- 6in / 1out HDMI (3D/ARC/CEC)
- Front HDMI input for quick connection of tablet, iPad/iPhone, camera, camcorder, etc.
- iPod / iPhone compatible USB input incl. iPad charging
- Multilingual Setup Assistant and Audyssey calibration makes hook up an easy task
- Multi room/Multi source
- Easy Remote Control and Marantz Remote App for advanced media browsing

EAN

EU	SR5007/N1B	4951035047408	Black
	SR5007/N1SG	4951035047415	Silver-Gold
UK	SR5007/T1B	4951035047408	Black
	SR5007/T1SG	4951035047415	Silver-Gold

www.marantz.eu

because music matters

SR5007

NETWORK AV RECEIVER



FEATURES	SR5007
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL liz	• / • / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX / MDAX2	- / •
NETWORK	
DLNA Certified	• (v1.5)
Network Audio: MP3 / WAV / AAC / FLAC / FLAC 192/24 / WMA	• / • / • / • / • / •
Gapless playback	• (firmware update)
Internet Radio	vTuner
Music service: last.fm* / Spotify*	• / •
Ethernet	•
OTHERS	
Bluetooth audio via RX101	optional
Auto speaker setup by microphone Audyssey MultEQ XT	•
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion CVBS > HDMI; Comp > HDMI	•
Analog to HDMI scaling	up to 4k
HDMI to HDMI scaling	up to 4k
Video processing	•
Picture adjust / Noise reduction	• / •
HDMI path though on stand-by	•
4k video pass through	•
3D video pass through	•
Audio Return Channel	•
On Screen Display: GUI / OSD	• / -
GUI overlay on HDMI	•
Setup Assistant (multilingual)	•
Variable cross over	•
Multiroom zones	1

* not available in all countries

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3 / 1
Component In / Out	2 / 1
HDMI In / Out	5+1 / 1
AUDIO	
Analogue In / Out	5 / 0
Digital Optical In / Out	2 / 0
Digital Coaxial In / Out	2 / 0
Multichannel Pre Out / Main In	• (7.2) / -
Subwoofer Out	2
7.1 multichannel input	•
OTHER	
M-XPoRT for RX101	•
Speaker A / B	•
Height speaker terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting) / Speaker C	• / •
Multi-Room Speaker Terminal	•
Marantz remote bus	•
IR Flasher In	•
Network: (IP-control / update)	• / •
RS232C (control / update)	• / •
USB firmware update	•
DC Triggers	•
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	• / • / - / • / •
USB Audio / Made for iPod / Works with iPhone	• / • / •
SPECIFICATIONS	
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)	100 W
70% Guarantee	•
Audio Signal to Noise Ratio	100 dB
FM Tuner	•
GENERAL	
Available colors: Black / Silver-Gold	• / •
System Remote Control	RC017SR
Power Consumption in	W 650
Standby Consumption in	W 0.2
Maximum Dimensions (W x D x H) in mm	440 x 339 x 161
Weight in kg	10.1

Design and specifications are subject to change by Marantz without notice.